## **Product Specifications**

### **FONE540**

- Wireless Bluetooth / USB Wired for PC
- Full duplex microphone array speakerphone
- Two omnidirectional microphones support 360° pickup
- Full duplex echo cancellation
- Advanced noise suppression
- Powerful wideband voice processing
- · Speaker volume: adjustable to 90 dB SPL at 0.5 m
- 3.5 mm line-in (aux) cable connects BYOD smartphones or PCs to use as speakerphones
- Touch controls for volume down/up, mute,
- phone input, call, and hang up • Can bridge phone-in and USB into one call

# USB

- Micro USB 2.0

## **Hardware Specifications**

- Processor: 3.2 GHz Intel<sup>®</sup> Core™ i5-4460 or later
- · 4 GB RAM
- USB port

## Security

Kensington slot

## System Requirements

- Windows® 7/10 or later
- Mac OS X v10.13 or later
- Google Chromebook™ version 76.0.3809.102 or later
- Android™ 6 or later

## **Power Supply**

- AC 100V to 240V, 50/60 Hz Consumption: 12V, 5A

### Free Applications for Meeting **Collaboration** (for Windows<sup>®</sup> and Mac Devices)

- PTZApp
- Upgrade firmware automatically or manually - Diagnose operating status
- EZLive
  - Real-time streaming / annotating / snapshots / video recording

## **Optional Accessories**

- Expansion speakerphone (10 m cable included), daisy-chain up to three speakerphones
- Two expansion microphones (two 5 m cables included), daisy-chain up to four microphones

## Warranty\*

· Camera/Speakerphone: 3+2 years · Accessories: 1 year

## **Compatible Applications**

Zoom, Microsoft® Teams, Skype for Business, WebRTC, Google Meet™, BlueJeans, Wirecast, Adobe<sup>®</sup> Connect™, Skype, vMix, GoToMeeting™ RingCentral, TrueConf, Cisco Webex<sup>®</sup>, LiveOn, XSplit, Vidyo, V-Cube, Microsoft® Lync™, Fuze, CyberLink U Meeting<sup>®</sup>, Intel<sup>®</sup> Unite™

202010

Connectivity

• 12V power adapter

or microphone)

• 3.5 mm line out

• UAC, plug and play

**Environmental Data** 

Control

PTZApp

Dimensions

Micro USB connector

· 3.5 mm phone-in jack

• LAN for IP remote access

· Expansion port (daisy-chain speakerphone

• Web UI: browser IP access via Chrome™

• Operation temperature: 0°C to 40°C

• Storage temperature: -20°C to 60°C Storage humidity: 20% to 80%

• Package dimensions: 259 x 259 x 171 mm

• Speakerphone: 220 x 181.5 x 49.5 mm/0.85 kg

• Micro USB 2.0 to Type-A cable (16 ft/5 m)

• 3.5 mm aux cable (3 ft/0.9 m)

Operation humidity: 20% to 80%

• Package weight: 1.93 kg

**Package Contents** 

• Speakerphone unit

Power adapter

• Warranty card

• Quick Start Guide

browser (Internet Explorer not supported)

# **Product Appearance**





Back

Distributor/Dealer



AVer ©2020 AVer Information Inc. All rights reserved. All brand names and logos are trademarks of their respective companies.



CEFC RoHS











Double-Tal

**Bluetooth**°





Clear Led



# **Ideal in Meeting Rooms of All Shapes and Sizes**

The FONE540 is a daisy-chainable USB speakerphone that enhances your audio conferencing experience in personal workspaces, huddle rooms, and medium-to-large conference rooms. Easy to plug in, install, and use, the FONE540 supplies business-class acoustics without creating extra work.



# speakerphone 🔵 mic 00000 000000

# **Expansion Speakerphones/Microphones** Adapt to Various Spaces

Embedded with daisy-chain technology, the FONE540 can be expanded by adding up to three additional speakerphones to provide full coverage in all kinds of rooms. Both microphones and speakerphones can also be added to the system, making it a perfect choice in any space.

# **Advanced Noise Suppression Achieves Amazing Acoustics**

Feeling irritated by background keyboard typing and air conditioning sounds during a conference call? The FONE540 silences the noise and guarantees unmatched audio clarity to free you from distractions.

# Flawless Audio for Fluid Communication

Do people on the other side of your audio meeting still have trouble hearing every word you say? With the FONE540 you won't have to repeat yourself anymore. Equipped with double-talk detection, the FONE540 makes every call feel like a face-to-face conversation.

# A Third Party Can Join Anytime, From Anywhere

The FONE540 speakerphone facilitates easy three-way calling. A third party can participate simply by calling a phone connected to the FONE540 by a 3.5 mm line-in jack. It's a simple yet effective way for three parties to enjoy a meeting with superior audio quality.

# **Smart Indicator Lights Clearly Display** the Speaker Status

There's no need to worry about whether everyone in the meeting knows if the FONE540 is on or off, muted or idle. Smart LED indicators enable people in every corner of the room determine the speakerphone's status with to determine .









